


CW see from the flange side



PIN LOCATION	COLOR	SWITCHING SEQUENCE			
		→ CW			
1	BROWN	-	+	+	-
2	RED	+	-	-	+
3	ORANGE	-	-	+	+
4	YELLOW	+	+	-	-

說明：搭配 $\frac{1}{8}$ "INCH管徑

MODEL		Motor Characteristics				THIRD ANGLE PROJECTION	製圖	JOANNE	Cheshire Electric Company, LLC		
JP42-E0G1B174		Resistance	Step Angle	Steps Revolution	流量(cc/min)	ALL DIMENSION ARE IN MM (UNLESS OTHERWISE SPECIFIED)	設計		Part No		
Constant current	24V 0.6A	10Ω	7.5°	48	3~80cc		審核		Name		REV. NO.
						繪製比例: 1:1	材料	完成時間	2012/12/3	Pump motor	A